

Line 6

HX One



1. GET THE FREE LINE 6 APPS

HX One uses **HX One Librarian**, not HX Edit. From the Line 6 Software page below, download it and **Line 6 Central**, which updates the firmware (free Line 6 account needed).

[Download the apps](#)

2. BACK UP, THEN UPDATE

Connect HX One by USB-C, not through a hub. In HX One Librarian, click **BACKUP** at the bottom, then **Save**. Install the latest firmware with Line 6 Central. Line 6 then asks for a factory reset: hold the **EFFECT** knob and **HOME** button while plugging in power. That erases your presets, so click **RESTORE**, pick your backup and click **Open**.

3. LOAD YOUR PRESETS

In HX One Librarian, click the preset you want to replace, then click **IMPORT** and choose a .hx1p file from the Presets folder of your download. Confirm the overwrite. Repeat for each preset. Your backup keeps the old ones safe.

4. TEST OUT YOUR NEW PRESETS

Press **ON** and **TAP | FLUX** together to open the Preset List. Turn the **EFFECT** knob to pick a preset and play. Share a clip? Tag the artist!

Troubleshooting Tips

HX One presets only work on HX One. They will not load in HX Edit, Helix or HX Stomp.

Import failed? Update the firmware with Line 6 Central and try again.

Update stuck or pedal not found? Unplug MIDI cables, use a USB-C cable 2 meters or shorter, and keep your laptop on power.

[HX One Manual](#)

Still stuck? Reach out to us at support@soundshop.co. We would love to help!

